

100W, Universal Input UPS/Battery Charger

BCH 100 Series



- Rugged industrial quality
- Conduction/convection cooled - no fan
- Fully protected
- Field proven design
- Low battery disconnect circuit

The BCH 100 is a compact DC output UPS system with external battery. The built-in battery charger provides 100W total power for the output and for float charging the battery. The unit has a low battery disconnect circuit to prevent damage to the battery by low discharge during prolonged AC failure. A built-in charger fail alarm (Fail Close) indicates either failure of the charger circuit or loss of AC input power. Any additional options are eliminated to keep the cost for this series low. The battery input is protected against accidental reverse battery connection by a crossbar diode and internal safety fuse. The battery must be fused externally directly to the battery. Low component count and the use of components with established reliability result in a high MTBF. The unit is manufactured at our plant under strict quality control.

GENERIC SPECIFICATIONS

Input

Mains Input:

95Vac to 264Vac universal 47 - 63Hz or 120Vdc to 360Vdc

Battery Input:

12V, 24V or 48V battery

Input Protection

AC Input

Inrush current limiting

Varistor

Internal safety fuse

Lower voltage than the specified minimum input will not damage the unit

Battery Input:

Internal safety fuse and crossbar diode

Low battery disconnect circuit disengages battery

Warning: Battery must be fused externally, directly at the battery

Input Isolation

2250VDC input to chassis

4300VDC input to output,

8mm spacing

500VDC output to chassis

Standards

Designed to meet EN 60950 and related standards

EMI

Meets EN 55022 Class B

Switching Frequency

47kHz +/- 2kHz

Output Voltages/Currents

13.8Vdc/8A, 27.6Vdc/4A or

55.2Vdc/2A. Adjustable $\pm 5\%$

Consult factory for other voltages

Output Separation Diode

Installed internally

Line/Load Regulation

$\pm 1.5\%$ combined from no load to full load including output separation diode

Output Ripple/Noise

Better than 1% of output voltage peak to peak or 0.2% RMS of the output voltage (20MHz BW)

Overload Protection

Rectangular current limiting with hiccup mode short circuit protection

Thermal shut-down with automatic recovery in case of insufficient cooling

Internal battery safety fuse on battery input

Output Overvoltage Protection

Double regulator loop, stable and independent of the main feedback loop

Efficiency

Typically 80 - 90% at full load depending on output

Operating Temperature

0°C to +50°C without derating. Extended temperature range available

Temperature Drift

0.03% per °C over operating temperature range

Cooling

Conduction to customer heatsink or chassis and natural convection

Environmental Protection

Basic ruggedizing
Additional ruggedizing and conformal coating available

Shock/Vibration

Designed to meet IEC 61373
Cat 1 A&B

Humidity

5 - 95% non-condensing

MTBF

150,000h at 45°C
Demonstrated MTBF is significantly higher

Indicators

Charger "ON" LED beside terminal block

Control input

None

Alarm Outputs

Charger Fail Alarm Form B (Fail close alarm)

Package/dimensions

F1: 114 x 51 x 201 mm (4.5" x 2" x 7.9") including terminal block and flanges
Mounting holes are clear

Weight

0.8 Kg (1.8 lb) approx.

Connections

9-pole barrier type terminal block with 3/8" spacing for all connections

RoHS Compliance

Fully compliant

Warranty

Two years subject to application within good engineering practice.

Enhancements to these general specifications and customizing can be accommodated upon request. Specifications subject to change.

Designer and manufacturer of quality converters, inverters, UPS systems, complete rack mount systems and DC-input fluorescent lamp inverters since 1982. Custom or standard. Absopulse is a BABT-approved Facility



ABOPULSE ELECTRONICS LTD

110 Walgreen Road

Ottawa, Ontario. K0A 1L0. CANADA

Tel: (613) 836-3511 Fax: (613) 836-7488

E-mail: absopulse@absopulse.com

<http://www.absopulse.com>