

150W, Universal Input UPS/Battery Charger

BCH 152 Series



- Rugged industrial quality
- Conduction/convection cooled - no fan
- Fully protected
- Field proven design
- Low battery disconnect circuit

The BCH 152 is a compact DC output UPS system with external battery. The built-in battery charger provides 150W total power for the output and for float charging the battery. The unit has a low battery disconnect circuit to prevent damage to the battery by low discharge during prolonged AC failure. A Low Battery Alarm provides warning before the disconnect circuit disengages the output. A built-in charger fail alarm indicates either failure of the charger circuit or loss of AC input power. The battery input is protected against accidental reverse battery connection by a crossbar diode and internal safety fuse. The battery must be fused externally, directly at the battery. Low component count, large design headroom, and the use of components with established reliability result in a high MTBF. The unit is manufactured at our plant under strict quality control.

SPECIFICATIONS

Input Voltage

Mains Input:

95Vac to 264Vac universal 47 - 63Hz

Battery Input:

12V, 24V or 48V battery

Input Protection

AC Input

Inrush current limiting

Varistor

Internal safety fuse

Lower voltage than the specified minimum input will not damage the unit

Battery Input:

Internal safety fuse and crossbar diode

Low Battery Disconnect circuit disengages battery

Current Drain From Battery at zero output load:

13.8V version: 100mA

27.6V version: 50mA

55.2V version: 25mA

Warning: Battery must be fused externally, directly at the battery

Input Isolation

2250VDC input to chassis

4300VDC input to output,

8mm spacing

500VDC output to chassis

Standards

Meets EN60950 and corresponding

UL and CSA standards

EMI

EN55022 Class A with margins

Switching Frequency

47kHz +/- 2kHz

Output Voltages/Currents

13.8V float voltage (12V battery) or

27.6V float voltage (24V battery) or

55.2V float voltage (48V battery)

The output is isolated, either

terminal can be grounded

Other outputs available on request

Output Separation Diode

Installed internally

Line/Load Regulation

±1.5% combined from no load to full load including built in separation diode

Output Ripple/Noise

Better than 1% of output voltage

peak to peak or 0.2% RMS of the

output voltage (20MHz BW)

Overload Protection (without battery)

Rectangular current limiting with

hiccup type short-circuit protection

Internal safety fuse on battery input

In the case of an accidental shorting

of the output, the external battery

fuse will blow.

Output Overvoltage Protection

Double regulator loop, stable

and independent of the

main feedback loop

Efficiency

Min 80% at full load

Operating Temperature

0°C to +50°C for full specification

with natural convection cooling

Wider temperature ranges

available on request

Battery Temp. Compensation

Available as an option

Temperature Drift

0.03% per °C over operating

temperature range (without BTC)

Cooling

Conduction to customer heatsink

or chassis and natural convection

Environmental Protection

Basic ruggedizing

Additional ruggedizing and

conformal coating available

Shock/Vibration

IEC 61373 Cat 1 A&B

Humidity

5 - 95% non-condensing

MTBF

130,000h at 45°C

Demonstrated MTBF is

significantly higher

Indicators

Charger ON LED visible through the cooling slots

Alarm Outputs

Charger/AC fail alarm, Fail Close

Low Battery Alarm, Fail Close

with common return

Package/Dimensions (W x H x L)

F2: 114 x 58 x 256 mm

(4.5" x 2.3" x 10.1") including

terminal block and flanges.

Mounting holes are clear

Weight

1.2 kg (2.6 lb) approx.

Connections

12-pole terminal block with 7.62mm

spacing for all connections, including

alarm

RoHS Compliance

Fully compliant

Warranty

Two years subject to application

within good engineering practice

Terminal Block Pin-out

OUTPUT		BATTERY		ALARM			BTC		AC INPUT		
+	-	-	+	COM	LBA F/C	CFA F/C	TS	TS	GND	N	PH
1	2	3	4	5	6	7	8	9	10	11	12

Enhancements to these general specifications and customizing can be accommodated upon request. Specifications are subject to change.

Designer and manufacturer of quality converters, inverters, UPS systems, complete rack mount systems and DC-input fluorescent lamp inverters since 1982. Custom or standard. Absopulse is a BABT-approved facility.



ABSOPULSE ELECTRONICS LTD

110 Walgreen Road, Ottawa, Ontario | K0A 1L0 | CANADA

Tel: +1-613-836-3511 | Fax: +1-613-836-7488

E-mail: absopulse@absopulse.com | <http://www.absopulse.com>